Federal Implementation Guideline for Electronic Data Interchange

ASC X12 003040 Transaction Set 838 Trading Partner Profile (Confirmation of Vendor Registration)

Implementation Convention

NIST

U.S. DEPARTMENT OF COMMERCE
Technology Administration
National Institute of
Standards and Technology

Federal Implementation Guideline for Electronic Data Interchange

ASC X12 003040 Transaction Set 838 Trading Partner Profile (Confirmation of Vendor Registration)

Implementation Convention

Electronic Commerce Acquisition Program Management Office
Standard Management Committee - Secretariat
National Institute of Standards and Technology
Gaithersburg, MD 20899-0001

Editor: Dr. Jean-Philippe Favreau

August 1995

838 Trading Partner Profile

Introduction:

This Draft Standard for Trial Use contains the format and establishes the data contents of the Trading Partner Profile Transaction Set (838) for use within the context of an Electronic Data Interchange (EDI) environment. This transaction set can be used to request, change, verify or transmit business profile information to or from a trading partner. This information can be used by the receiver to facilitate the processing of the sender's business transactions. The transaction set may be used to convey government survey information, business classification, general survey information, summary supplier ratings, changes in the EDI environment information, tax information, entity relationships, and general business profile information to update automated information data bases between trading partners.

Notes:

1. Use this transaction set to acknowledge the successful processing of a previously received request for registration as a Federal Government trading partner.

2. Use this transaction set to inform a registering party that a request to register was partially processed. When used in this manner, use the transaction set to provide the reason(s) why the request could not be fully processed.

3. Successful confirmation will be determined in part, only upon the validation of the registering party's DUNS and TIN numbers, as provided in the 838 contractor registration transaction set.

4. Validation of registration will take some time, therefore, registering parties should not anticipate an immediate confirmation of successful or partial registration. Registrants are advised to wait until they have received an official response from the registration process.

5. Do not use this transaction set to notify a registering party of an unsuccessful registration. Use the 824 transaction set to notify a registrant of an application problem that precludes a successful registration.

Heading:

	Pos. No.	Seg. ID	Name	Req. Des.	Max.Use	Loop Repeat	Notes and Comments
	010	ST	Transaction Set Header	M	1		
	020	BTP	Beginning Segment For Trading Partner Profile	M	1		
N/U	021	REQ	Request Information	O	1		
	025	PER	Administrative Communications Contact	O	1		
			LOOP ID - LX			>1	
	029	LX	Assigned Number	O	1		
			LOOP ID - PLA			>1	
	030	PLA	Place or Location	O	1		
N/U	040	LCD	Place/Location Description	O	>1		
N/U	050	LIN	Item Identification	O	>1		
			LOOP ID - N1			>1	

	060	N1	Name	O	1	
N/U	070	N2	Additional Name Information	O	2	
N/U	080	N3	Address Information	O	2	
N/U	090	N4	Geographic Location	O	1	
	100	N9	Reference Number	O	>1	
N/U	110	PER	Administrative Communications Contact	O	>1	
N/U	120	CUR	Currency	O	>1	
N/U	130	TAX	Tax Reference	O	>1	
N/U	140	FOB	F.O.B. Related Instructions	O	>1	
N/U	150	ITD	Terms of Sale/Deferred Terms of Sale	O	>1	
N/U	160	TD5	Carrier Details (Routing Sequence/Transit Time)	O	>1	
N/U	170	FBB	Foreign and Industry Business	O	>1	n1
N/U	171	DTM	Date/Time Reference	O	2	
N/U	172	LCD	Place/Location Description	O	>1	

LOOP ID - TPD					>1	
	180	TPD	Trading Partner Detail	O	1	
N/U	190	N9	Reference Number	O	>1	
N/U	200	PID	Product/Item Description	O	>1	
N/U	210	DTM	Date/Time Reference	O	>1	
N/U	215	LS	Loop Header	O	1	

LOOP ID - TUD					>1	
N/U	220	TUD	Trade Union Data	O	1	
N/U	230	DTM	Date/Time Reference	O	>1	
N/U	240	N1	Name	O	1	
N/U	250	N2	Additional Name Information	O	2	
N/U	260	N3	Address Information	O	2	
N/U	270	N4	Geographic Location	O	1	
N/U	280	PER	Administrative Communications Contact	O	>1	
N/U	285	LE	Loop Trailer	O	1	

LOOP ID - SPR					>1	
N/U	290	SPR	Supplier Rating	O	1	
N/U	300	N9	Reference Number	O	>1	
N/U	310	DTM	Date/Time Reference	O	>1	

LOOP ID - PAM					>1	
N/U	320	PAM	Period Amount	O	1	
N/U	330	DTM	Date/Time Reference	O	>1	
N/U	340	TAX	Tax Reference	O	>1	
N/U	350	CUR	Currency	O	>1	

			LOOP ID - TXN			>1
N/U	360	TXN	Transaction Capabilities	O	1	
N/U	370	N9	Reference Number	O	>1	
N/U	380	DTM	Date/Time Reference	O	>1	
			LOOP ID - ENE			>1
N/U	390	ENE	Electronic Systems Environment	O	1	
			LOOP ID - N1			>1
N/U	400	N1	Name	O	1	
N/U	410	N2	Additional Name Information	O	2	
N/U	420	N3	Address Information	O	2	
N/U	430	N4	Geographic Location	O	1	
N/U	440	TPD	Trading Partner Detail	O	>1	
N/U	450	PID	Product/Item Description	O	>1	
N/U	460	N9	Reference Number	O	>1	
N/U	470	PER	Administrative Communications Contact	O	>1	
			LOOP ID - TXN			>1
N/U	480	TXN	Transaction Capabilities	O	1	
N/U	490	N9	Reference Number	O	>1	
N/U	500	DTM	Date/Time Reference	O	>1	
N/U	510	ERI	Entity Relationship	O	>1	
N/U	520	AMT	Monetary Amount	O	>1	
	530	SE	Transaction Set Trailer	M	1	

Transaction Set Notes

1. With each occurence of the PLA loop, the sum of FBB03 for separately identified countries cannot exceed 100.

Segment: **ST** **Transaction Set Header**
Position: **010**
Loop:
Level: Heading
Usage: Mandatory
Max Use: 1
Purpose: To indicate the start of a transaction set and to assign a control number
Notes:
Syntax Notes:
Semantic Notes: **1**   The transaction set identifier (ST01) used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the invoice transaction set).
Comments:

Data Element Summary

	Ref. Des.	Data Element	Name	Attributes		
M	ST01	143	**Transaction Set Identifier Code**	M	ID	3/3
			Code uniquely identifying a Transaction Set.			
			838 X12.17 Trading Partner Profile			
M	ST02	329	**Transaction Set Control Number**	M	AN	4/9
			Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set			
			Use to transmit a unique number assigned by the originator of the transaction set. This number may be system generated.			

Segment:	**BTP** Beginning Segment For Trading Partner Profile		
Position:	020		
Loop:			
Level:	Heading		
Usage:	Mandatory		
Max Use:	1		
Purpose:	To indicate the type and purpose of the profile data		
Notes:	When cancelling a previously transmitted confirmation of registration use of the		

transaction set, use BTP07/08/09 to carry the number, date and time of the transmission being cancelled.

Syntax Notes:	1	If BTP08 is present, then BTP07 is required.
	2	If BTP09 is present, then BTP08 is required.
Semantic Notes:	1	BTP01 indicates the purpose of this EDI transmission.
	2	BTP02 is the identifying number of this transaction.
	3	BTP03 and BTP04 are the transaction set date and time.
	4	BTP06 indicates the status of the data content within the transaction.
	5	BTP07 indicates reference number or previous reference number associated with

this transaction.

	6	BTP08 and BTP09 are date and time associated with BTP07.
Comments:		

Data Element Summary

	Ref. Des.	Data Element	Name	Attributes		
M	BTP01	353	**Transaction Set Purpose Code**	M	ID	2/2

Code identifying purpose of transaction set.

> 00   Original
>
> *Use to indicate the original confirmation of a request for registration. Use if the transmission contains either an acknowledgment of a successful registration or a partial acceptance of a request for registration.*
>
> 01   Cancellation
>
> *Use to indicate a cancellation of a previously transmitted response to a request for registration.*
>
> 07   Duplicate
>
> *Use to indicate a duplicate response to a request for registration. Use only when informed that the original response to a request for registration was not received.*

M	BTP02	127	**Reference Number**	M	AN	1/30

Reference number or identification number as defined for a particular Transaction Set, or as specified by the Reference Number Qualifier.

Use to indicate a unique number, assigned by the originator of the transaction set, that can be used as a reference in a subsequent transaction set. This number may be system generated.

M	BTP03	373	**Date**	M	DT	6/6

Date (YYMMDD).

Use to indicate the date the transaction set was created.

M	BTP04	337	**Time**	M	TM	4/8

Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59),

S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)

Use to indicate the time the transaction set was created. Use local time. Use only the HHMM format (e.g., 1030, 0925, etc.).

| M | BTP05 | 640 | **Transaction Type Code** | M | ID | 2/2 |

Code specifying the type of transaction.

TP   Trading Partner Information

| M | BTP06 | 353 | **Transaction Set Purpose Code** | O | ID | 2/2 |

Code identifying purpose of transaction set.

11   Response

Use to indicate that this transmission is a response to a previously submitted initial request to register, or a change to, or annual renewal of a previously successful registration.

| M | BTP07 | 127 | **Reference Number** | X | AN | 1/30 |

Reference number or identification number as defined for a particular Transaction Set, or as specified by the Reference Number Qualifier.

Use in other than cancellations, to indicate the reference number contained in BTP02 of the request for registration transaction set. Use in cancellations to indicate the number of the cancelled transmission.

| M | BTP08 | 373 | **Date** | X | DT | 6/6 |

Date (YYMMDD).

Use in other than cancellations, to indicate the date contained in BTP03 of the request for registration transaction set. Use in cancellations to indicate the date of the cancelled transmission.

| M | BTP09 | 337 | **Time** | O | TM | 4/8 |

Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)

Use in other than cancellations, to indicate the time in BTP04 of the request for registration transaction set. Use in cancellations to indicate the time of the cancelled transmission.

Segment: **PER**Administrative Communications Contact
Position: 025
Loop:
Level: Heading
Usage: Optional
Max Use: 1
Purpose: To identify a person or office to whom administrative communications should be directed

Notes: Use this segment to provide the toll free commercial telephone number for registering parties to call to obtain information regarding doing business using Electronic Data Interchange (EDI) or to inquire about their registration.

Syntax Notes: **1** If either PER03 or PER04 is present, then the other is required.
2 If either PER05 or PER06 is present, then the other is required.

Semantic Notes:
Comments:

Data Element Summary

	Ref. Des.	Data Element	Name		Attributes	
M	PER01	366	Contact Function Code	M	ID	2/2

Code identifying the major duty or responsibility of the person or group named.

EA   EDI Coordinator

Use to indicate the Electronic Commerce Information Center contact.

	Ref. Des.	Data Element	Name		Attributes	
X	PER02	93	Name	O	AN	1/35

Free-form name.

	PER03	365	Communication Number Qualifier	X	ID	2/2

Code identifying the type of communication number.

TE   Telephone

Use to indicate the toll free commercial telephone number. Ensure the 800 area code is included.

	PER04	364	Communication Number	X	AN	1/80

Complete communications number including country or area code when applicable.

X	PER05	365	Communication Number Qualifier	X	ID	2/2

Code identifying the type of communication number.

Refer to 003040 Data Element Dictionary for acceptable code values.

X	PER06	364	Communication Number	X	AN	1/80

Complete communications number including country or area code when applicable.

Segment: **LX** Assigned Number
Position: **029**
Loop: LX
Level: Heading
Usage: Optional
Max Use: 1
Purpose: To reference a line number in a transaction set.
Notes: Use to indicate the number of the iteration of the LX loop. For example, in the first iteration of the LX loop, insert the number 1 in LX01, in the second iteration of the LX loop (if there is a second iteration in the transmission), insert the number 2, and so on. This number may be system generated.
Syntax Notes:
Semantic Notes:
Comments:

Data Element Summary

	Ref. Des.	Data Element	Name	Attributes		
M	LX01	554	**Assigned Number**	M	N0	1/6
			Number assigned for differentiation within a transaction set.			

	Segment:	**PLA** Place or Location
	Position:	**030**
	Loop:	PLA
	Level:	Heading
	Usage:	Optional
	Max Use:	1
	Purpose:	To indicate action to be taken for the location specified and to qualify the location specified
	Notes:	Use is required in original response to a registration request. Do not use in cancellation.
	Syntax Notes:	
	Semantic Notes:	1 PLA03 is the effective date for the action identified in PLA01.
		2 When used, PLA04 is the effective time for the action identified in PLA01.
	Comments:	

Data Element Summary

	Ref. Des.	Data Element	Name	Attributes		
M	PLA01	306	**Action Code**	M	ID	1/2

Code indicating type of action.

Use to identify the action being taken in the response as either a successful registration or an inability to register the requesting party. Identify by a code value in PLA02 the same code as used by the requesting party in the original request for registration transaction set. Also include the effective date of the decision to register or reject the request.

	IN	Interim

Use to indicate that the registration application has been partially accepted, but that there is some non-essential data under review.

	KA	Registration Confirmed

The application requesting registration was favorably acted upon and registration is confirmed

Use to indicate that a requesting party has been successfully registered.

	Ref. Des.	Data Element	Name	Attributes		
M	PLA02	98	**Entity Identifier Code**	M	ID	2/2

Code identifying an organizational entity, a physical location, or an individual

	KK	Registering Party

The party requesting registration into a system

Use to identify the party submitting the request to register transaction set.

	Ref. Des.	Data Element	Name	Attributes		
M	PLA03	373	**Date**	M	DT	6/6

Date (YYMMDD).

Use to indicate the effective date of the action described by the code value in PLA01.

	Ref. Des.	Data Element	Name	Attributes		
X	PLA04	337	**Time**	O	TM	4/8

Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)

X   PLA05   1203   Maintenance Reason Code   O   ID   2/3

Code identifying the reason for the maintenance change.

Refer to 003040 Data Element Dictionary for acceptable code values.

Segment: **N1** Name
Position: **060**
Loop: N1
Level: Heading
Usage: Optional
Max Use: 1
Purpose: To identify a party by type of organization, name and code
Notes: There must be at least one iteration of the N1 loop in each transaction set to carry the address of the requesting party.
Syntax Notes: 1 At least one of N102 or N103 is required.
2 If either N103 or N104 is present, then the other is required.
Semantic Notes:
Comments: 1 This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2 N105 and N106 further define the type of entity in N101.

Data Element Summary

	Ref. Des.	Data Element	Name		Attributes	
M	N101	98	**Entity Identifier Code**	M	ID	2/2
			Code identifying an organizational entity, a physical location, or an individual			
			KK Registering Party			
			The party requesting registration into a system			
			Use to identify the party submitting the request for registration.			
X	N102	93	**Name**	X	AN	1/35
			Free-form name.			
	N103	66	**Identification Code Qualifier**	X	ID	1/2
			Code designating the system/method of code structure used for Identification Code (67).			
			1 D-U-N-S Number, Dun & Bradstreet			
			Use, if applicable, to identify the party requesting registration.			
	N104	67	**Identification Code**	X	AN	2/17
			Code identifying a party or other code.			
X	N105	706	**Entity Relationship Code**	O	ID	2/2
			Code describing entity relationship.			
			Refer to 003040 Data Element Dictionary for acceptable code values.			
X	N106	98	**Entity Identifier Code**	O	ID	2/2
			Code identifying an organizational entity, a physical location, or an individual			
			Refer to 003040 Data Element Dictionary for acceptable code values.			

Segment:	**N9** Reference Number	
Position:	**100**	
Loop:	N1	
Level:	Heading	
Usage:	Optional	
Max Use:	>1	

Purpose: To transmit identifying numbers and descriptive information as specified by the reference number qualifier

Notes: Use this segment to provide a unique number assigned by the Federal Government to a successfully registered trading partner. Do not use if the registration is not successful.

Syntax Notes: 1 At least one of N902 or N903 is required.

2 If N906 is present, then N905 is required.

Semantic Notes: 1 N906 reflects the time zone which the time reflects.

Comments:

Data Element Summary

	Ref. Des.	Data Element	Name		Attributes	
M	N901	128	**Reference Number Qualifier**	M	ID	2/2
			Code qualifying the Reference Number.			
			EL Electronic device pin number			
			Use to provide a unique Trading Partner Identification Number (TPIN) to a successfully registering party.			
	N902	127	**Reference Number**	X	AN	1/30
			Reference number or identification number as defined for a particular Transaction Set, or as specified by the Reference Number Qualifier.			
X	N903	369	**Free-form Description**	X	AN	1/45
			Free-form descriptive text.			
X	N904	373	**Date**	O	DT	6/6
			Date (YYMMDD).			
X	N905	337	**Time**	X	TM	4/8
			Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)			
X	N906	623	**Time Code**	O	ID	2/2
			Code identifying the time. In accordance with International Standards Organization standard 8601, time can be specified by a + or - and an indication in hours in relation to Universal Time Coordinate (UTC) time. Since + is a restricted character, + and - are substituted by P and M in the codes that follow.			
			Refer to 003040 Data Element Dictionary for acceptable code values.			

Segment: **TPD** Trading Partner Detail
Position: **180**
Loop: TPD
Level: Heading
Usage: Optional
Max Use: 1
Purpose: To describe attribute of a trading partner
Notes: Use only in unsuccessful registrations, to indicate the reason(s) why the request to register could not be completely processed.
Syntax Notes: **1** If either TPD02 or TPD03 is present, then the other is required.
Semantic Notes:
Comments:

Data Element Summary

	Ref. Des.	Data Element	Name	Attributes		
M	TPD01	349	**Item Description Type**	M	ID	1/1

Code indicating the format of a description.

       F   Free-form

X	TPD02	23	**Commodity Code Qualifier**	X	ID	1/1

Code identifying the commodity coding system used for Commodity Code.

Refer to 003040 Data Element Dictionary for acceptable code values.

X	TPD03	22	**Commodity Code**	X	AN	1/16

Code describing a commodity or group of commodities.

	TPD04	352	**Description**	O	AN	1/80

A free-form description to clarify the related data elements and their content.

Use to advise the registrant of a partial registration by indicating the nature of the data under review, or the problem precluding full registration. Use also to inform partially accepted registrants that they can inquire about the status of their registration by calling the EDI help desk. The telephone number is to be provided in the 1/PER/025 segment.

Segment: **SE** **Transaction Set Trailer**
Position: **530**
Loop:
Level: Heading
Usage: Mandatory
Max Use: 1
Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments).
Notes:
Syntax Notes:
Semantic Notes:
Comments: **1** SE is the last segment of each transaction set.

Data Element Summary

	Ref. Des.	Data Element	Name	Attributes		
M	SE01	96	**Number of Included Segments**	M	N0	1/10

Total number of segments included in a transaction set including ST and SE segments.

Use to indicate the total number of segments included in the transmission including the ST and SE segments.

M	SE02	329	**Transaction Set Control Number**	M	AN	4/9

Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set

Use to transmit the same unique control number assigned by the originator of the transaction set, as the control number cited in ST02.

838 TRANSACTION SET USAGE

TRADING PARTNER PROFILE

Usage of the segments and data elements arrayed in alphabetical order by information content.

INFORMATION CONTENT	TS POS. NO.	SEGMENT/ DATA ELEMENT	O R I G	C A N C	D U P L	COMMENTS
ACTION CODE/ENTITY/EFFECTIVE DATE	1/030	PLA01/02/03	R		R	Identify the action being taken for either a successful registration or an inability to register. Include the effective date of the decision to register or reject.
ASSIGNED NUMBER	1/029	LX01	R	R	R	Loop iterations.
DATE -PREVIOUS TRANSACTION	1/020	BTP08	R	R	R	Use to indicate the date contained in BTP03. Use in cancellations to indicate the date of canceled transmission..
DATE CREATED	1/020	BTP03	R	R	R	The date the transaction set was created.
DESCRIPTION OF REASON FOR INCOMPLETE REGISTRATION	1/180	TPD01	R *	O	O	*Required if PLA01 is IN
NUMBER OF INCLUDED SEGMENTS	1/530	SE01	R	R	R	Total # of segments included in the transmission including the ST and SE segments.
PHONE-INFORMATION CONTACT FOR EC	1/025	PER01/03/04	O	O	O	Information Contact Toll free number.
REFERENCE NUMBER	1/020	BTP02	R	R	R	A unique #, assigned by the originator of the transaction set, that can be used as a reference in a subsequent transaction set.
REFERENCE NUMBER-PREVIOUS TRANSACTION	1/020	BTP07	R	R	R	Use to indicate the reference # contained in BTP02. Use in cancellation to indicate the number of the canceled transmission..
REFERENCE NUMBER-TPIN	1/100	N901/02	O	O	O	Cite code.
REGISTERING PARTY	1/060	N101/03/04	R	R	R	Cite code (DUNS).
TIME	1/020	BTP04	R	R	R	The Time the transaction set was created. Use local time, HHMM format.
TIME- PREVIOUS TRANSACTION	1/020	BTP09	R	R	R	Use to indicate the time in BTP04. Use in cancellations to indicate the time of the canceled transmission.
TRANSACTION SET CONTROL NUMBER	1/010	ST02	R	R	R	A unique # assigned by the originator of the transaction set.
TRANSACTION SET CONTROL NUMBER	1/530	SE02	R	R	R	Transmit the same unique control number assigned by the originator of the transaction set, in ST02.
TRANSACTION SET IDENTIFIER CODE	1/010	ST01	R	R	R	

TRANSACTION SET PURPOSE CODE	1/020	BTP01	R	R	R	Original, Cancellation, Duplicate.
			00	01	07	
TRANSACTION SET PURPOSE CODE	1/020	BTP06	R	R	R	Response (11).
TRANSACTION TYPE CODE	1/020	BTP05	R	R	R	Cite code TP.

838 TRANSACTION SET USAGE

TRADING PARTNER PROFILE

Usage of the segments and data elements arrayed in transaction set order.

TS POS. NO.	SEGMENT/ DATA ELEMENT	INFORMATION CONTENT	O R I G G	C A N C	D U P L	COMMENTS
1/010	ST01	TRANSACTION SET IDENTIFIER CODE	R	R	R	
1/010	ST02	TRANSACTION SET CONTROL NUMBER	R	R	R	A unique # assigned by the originator of the transaction set.
1/020	BTP01	TRANSACTION SET PURPOSE CODE	R 0 0	R 0 1	R 0 7	Original, Cancellation, Duplicate.
1/020	BTP02	REFERENCE NUMBER	R	R	R	A unique #, assigned by the originator of the transaction set, that can be used as a reference in a subsequent transaction set.
1/020	BTP03	DATE CREATED	R	R	R	The date the transaction set was created.
1/020	BTP04	TIME	R	R	R	The Time the transaction set was created. Use local time, HHMM format.
1/020	BTP05	TRANSACTION TYPE CODE	R	R	R	Cite code TP.
1/020	BTP06	TRANSACTION SET PURPOSE CODE	R	R	R	Response (11).
1/020	BTP07	REFERENCE NUMBER-PREVIOUS TRANSACTION	R	R	R	Use to indicate the reference # contained in BTP02. Use in cancellation to indicate the number of the canceled transmission..
1/020	BTP08	DATE -PREVIOUS TRANSACTION	R	R	R	Use to indicate the date contained in BTP03. Use in cancellations to indicate the date of canceled transmission..
1/020	BTP09	TIME- PREVIOUS TRANSACTION	R	R	R	Use to indicate the time in BTP04. Use in cancellations to indicate the time of the canceled transmission.
1/025	PER01/03/04	PHONE-INFORMATION CONTACT FOR EC	O	O	O	Information Contact Toll free number.
1/029	LX01	ASSIGNED NUMBER	R	R	R	Loop iterations.
1/030	PLA01/02/03	ACTION CODE/ ENTITY/EFFECTIVE DATE	R		R	Identify the action being taken for either a successful registration or an inability to register. Include the effective date of the decision to register or reject.
1/060	N101/03/04	REGISTERING PARTY	R	R	R	Cite code (DUNS).
1/100	N901/02	REFERENCE NUMBER-TPIN	O	O	O	Cite code.

1/180	TPD01	DESCRIPTION OF REASON FOR INCOMPLETE REGISTRATION	R *	O	O	*Required if PLA01 is IN
1/530	SE01	NUMBER OF INCLUDED SEGMENTS	R	R	R	Total # of segments included in the transmission including the ST and SE segments.
1/530	SE02	TRANSACTION SET CONTROL NUMBER	R	R	R	Transmit the same unique control number assigned by the originator of the transaction set, in ST02.